


# POWER PROVIDER



# SINGO 1000



**Camping Fridge**  
40 Watts  
± 72 Hours



**Fridge**  
350W  
± 48 Hours



**Hairdryer**  
1200W  
± 35 Min



**Air-Fryer**  
1500W  
± 55 min



**TV & DSTV**  
120W  
± 7 Hours



**Desktop**  
100W  
± 9 Hours

## Powerful Performance



Power high watt electrical devices up to **2000W**

Automotive Grade  
**1008 Wh**  
with  
**3000+ cycles**  
**LiFePO4 Battery**



### Seamless Power, Limitless Possibilities

**< 10ms auto-switch**  
The bi-directional inverter ensures your electronics and appliances receives a continuous clean and uninterrupted pure sine wave power supply.

### No adapter required




No adapter needed with South African Plug sockets, multiple output ports & wireless charging for your phone

		SINGO 1000
AC OUTPUT	Nominal AC Power (W)	1000
	AC Boost (W)	2000
	Surge Power (W)	3000
AC INPUT	AC Charging Power (W)	Super Charge (800W)
	Nominal Voltage (VAC)	220
BATTERY INPUT	Battery Input Nominal Voltage	22.5
	Battery Capacity (Wh)	1008
	Battery Cell Chemistry	Lithium Iron Phosphate (LiFePo4)
	Cycle Life at 95% DoD	3000+
DC INPUT	Max. Car Charging Input Power (W)	120
	Max. Solar Charging Input Power	10-30V; 10A / 200W
DC OUTPUT	USB-A (X1)	12.5W, 5V, 2.5A
	USB Quick Charge 3.0 (x2)	28W each, (5V, 9V, 12V), 2.4A
	USB Type-C (x2)	100W each, (5V, 9V, 12V, 20V), 5A
	Car Port and DC Port	132W, 13.2V, 10A
Weight (kg)		11.1

## Re-charge Faster, Go Further

Re-charge at 800W from 0 - 100% in only  
**90 Min**



without damaging the battery

## Stay in Control, Everywhere!

Download the Singo App for iOS or Android and experience the freedom of 24/7 monitoring & control.