

POWER PROVIDER



SINGO 600

 Camping Fridge 40 Watts ± 48 Hours	 Fridge 350W ± 12 Hours	 O2 Machine 300W ± 1.5 Hours
 Wi-Fi 20W ± 30 Hours	 TV & DSTV 120W ± 3.5 - 4 Hours	 Desktop 100W ± 5 Hours

Powerful Performance

Power high watt electrical devices up to **1000W**

Automotive Grade
672 Wh
 with
3000+ cycles
LiFePO4 Battery

Seamless Power, Limitless Possibilities
< 10ms auto-switch
 The bi-directional inverter ensures your electronics and appliances receives a continuous clean and uninterrupted pure sine wave power supply.

No adapter required

No adapter needed with South African Plug sockets, multiple output ports & wireless charging for your phone

		SINGO 600
AC OUTPUT	Nominal AC Power (W)	600
	AC Boost (W)	1000
	Surge Power (W)	1800
AC INPUT	AC Charging Power (W)	Super Charge (600W)
	Nominal Voltage (VAC)	220
BATTERY INPUT	Battery Input Nominal Voltage	22.5
	Battery Capacity (Wh)	672
	Battery Cell Chemistry	Lithium Iron Phosphate (LiFePo4)
	Cycle Life at 95% DoD	3000+
DC INPUT	Max. Car Charging Input Power (W)	120
	Max. Solar Charging Input Power	10-30V; 10A / 200W
DC OUTPUT	USB-A (X1)	12.5W, 5V, 2.5A
	USB Quick Charge 3.0 (x2)	28W each, (5V, 9V, 12V), 2.4A
	USB Type-C (x2)	100W each, (5V, 9V, 12V, 20V), 5A
	Car Port and DC Port	132W, 13.2V, 10A
Weight (kg)		8.8

Re-charge Faster, Go Further

Re-charge at 600W from 0 - 100% in only

90 Min

without damaging the battery

Stay in Control, Everywhere!

Download the Singo App for iOS or Android and experience the freedom of 24/7 monitoring & control.

